

Electric Vibrator Mount Kits

MICRO™ SERIES ELECTRIC VIBRATORS

VIBRATOR	BRACKET
NEA 504	MB-6
NEA/NEG 5020, 5050, 5060	MB-12

XHD™ EXTRA HEAVY DUTY ELECTRIC VIBRATORS

VIBRATOR	BRACKET
XHD-1.5/2/2.5T	MB-18
XHD-5/8T	MB-30
XHD-C12/16/24T	MB-36
XHD-C30/36T	MB-48

XHA™ EXTRA HI-AMPLITUDE ELECTRIC VIBRATORS

VIBRATOR	BRACKET
XHA-0.5/1.5/2T	MB-18
XHA-3.5/6.5/8.5T	MB-30
XHA-C11.5T	MB-36

Electric Vibrator Mount Kits

VIBRATOR MOUNT BRACKET DIMENSIONS

BRACKET	A	B	C	D	E	F	G
MB-6	6(152)	4.25(108)	6(152)	3.88(98.4)	0.19(4.76)	1.5(38.1)	0.19(4.76)
MB-12	12(305)	5.5(140)	6(152)	5(127)	0.25(6.35)	1.5(38.1)	0.25(6.35)
MB-18	18(457)	5.5(140)	6(152)	5(127)	0.25(6.35)	1.5(38.1)	0.38(9.65)
MB-30	30(762)	7.25(184)	7.5(191)	6.5(165)	0.38(9.65)	1.5(38.1)	0.38(9.65)
MB-36	36(914)	8.75(222)	11(279)	8(203)	0.38(9.65)	1.5(38.1)	0.5(12.7)
MB-48	48(914)	8.75(222)	11(279)	8(203)	0.38(9.65)	1.5(38.1)	0.5(12.7)

STANDARD "H" TYPE VIBRATOR MOUNT BRACKET

